



ⓘ Discontinued

### Main

|                           |  |
|---------------------------|--|
| Range                     | TeSys  |
| Device short name         | GV3A   |
| Product or component type | Auxiliary contact block  |
| Product compatibility     | GV3ME  |
| Mounting location         | Right side   |
| Pole contact composition  | 1 NO + 1 NC  |
| Connections - terminals   | Screw clamp terminals 1 cable(s) 1...2.5 mm <sup>2</sup> solid<br>Screw clamp terminals 2 cable(s) 1...2.5 mm <sup>2</sup> solid<br>Screw clamp terminals 1 cable(s) 0.75...2.5 mm <sup>2</sup> flexible without cable end<br>Screw clamp terminals 2 cable(s) 0.75...2.5 mm <sup>2</sup> flexible without cable end<br>Screw clamp terminals 1 cable(s) 0.75...2.5 mm <sup>2</sup> flexible with cable end<br>Screw clamp terminals 2 cable(s) 0.75...1.5 mm <sup>2</sup> flexible with cable end |
| Quantity per set          | Set of 10  |

### Complementary

|                                |   |
|--------------------------------|---|
| Standards                      | 600 V conforming to UL 508<br>690 V conforming to IEC 60947-1<br>600 V conforming to CSA C22.2 No 14  |
| [Ue] rated operational voltage | 48...690 V AC<br>24...220 V DC  |
| Protection type                | GB2CB... circuit breaker<br>GG fuse 6 A   |
| Utilisation category           | 350 VA at 48 V AC-11 - electrical durability: 100000 cycles<br>700 VA at 440 V AC-11 - electrical durability: 100000 cycles<br>700 VA at 500 V AC-11 - electrical durability: 100000 cycles<br>400 VA at 690 V AC-11 - electrical durability: 100000 cycles<br>500 VA at 110...127 V AC-11 - electrical durability: 100000 cycles<br>800 VA at 220...240 V AC-11 - electrical durability: 100000 cycles<br>850 VA at 380...415 V AC-11 - electrical durability: 100000 cycles |
| Utilisation category           | 180 W at 24 V DC-11 - electrical durability: 100000 cycles<br>240 W at 48 V DC-11 - electrical durability: 100000 cycles<br>180 W at 60 V DC-11 - electrical durability: 100000 cycles  |

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

140 W at 110 V DC-11 - electrical durability: 100000 cycles  
120 W at 220 V DC-11 - electrical durability: 100000 cycles

## Environment

|                              |                    |
|------------------------------|--------------------|
| Environmental characteristic | Normal environment |
|------------------------------|--------------------|

## Packing Units

|                  |          |
|------------------|----------|
| Package 1 Weight | 0.038 kg |
| Package 1 Height | 0.150 dm |
| Package 1 width  | 0.850 dm |
| Package 1 Length | 0.700 dm |



## Offer Sustainability

|                            |   |
|----------------------------|---|
| Sustainable offer status   | Green Premium product   |
| REACH Regulation           | <a href="#">REACH Declaration</a>   |
| EU RoHS Directive          | Compliant<br><a href="#">EU RoHS Declaration</a>  |
| Mercury free               | Yes   |
| RoHS exemption information | <a href="#">Yes</a>   |
| China RoHS Regulation      | <a href="#">China RoHS declaration</a><br>Product out of China RoHS scope. Substance declaration for your information       |
| Environmental Disclosure   | <a href="#">Product Environmental Profile</a>   |
| WEEE                       | The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins |

## Contractual warranty

|          |           |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

## GV3A01 is replaced by the following group of products:

|   |   |
|---|---|
|  | <b>Add-on auxiliary blocks GVAE11</b><br>TeSys GV2 & GV3 - auxiliary contact - 1 NO + 1 NC<br>Qty 1       |
|  | <b>Add-on auxiliary blocks GVAN11</b><br>TeSys GV2 & GV3 - auxiliary contact block - 1 NO + 1 NC<br>Qty 1 |

Reason for Substitution: End of life | Substitution date: 04 January 2020 | Partial substitution, GVAE11 is front mounting

## Or GV3A01 is replaced by the following group of products:



### Add-on auxiliary blocks GVAE11

TeSys GV2 & GV3 - auxiliary contact - 1 NO + 1 NC

Qty 1



### Add-on auxiliary blocks GVAN11

TeSys GV2 & GV3 - auxiliary contact block - 1 NO + 1 NC

Qty 1

Reason for Substitution: End of life | Substitution date: 04 January 2020 | Partial substitution, GVAN11 is LH side mounting